

## EF2800i

Type	Inverter
Rated Voltage	230V
Frequency	50Hz
Rated Output	2500 Watts
Max Output	2800 Watts
DC Output	None
Engine Type	OHV MZ175 Air Cooled
Displacement	171cc
Max Output	4kW (5.5hp) @4000rpm
Starting System	Recoil
LxWxH (mm)	487x395x425
Dry Weight	29kg
Fuel Tank Capacity	9.7L
Operating Hours (1/4 Load)	17hr (Eco On)
Noise Level (1/4 Load)	60dBA (7m)
Noise Level (Full Load)	67dBA (7m)
Brushless Alternator	•
Auto Decompressor	•
Electric Starter	
Circuit Breaker	Electronic
Fuel Level Gauge	•
Oil Level Warning	•
Voltage Meter	
Pilot Lamp	•
Noise Block™	
Economy Idle Control	•
Twin Tech™ (Parallel Use)	
Transportation Kit	
Remote Starter Kit	
AC Plug	•
DC Charging Cord	

## EF2800i

## 2.8KVA INVERTER GENERATOR

Big power in a small, lightweight package. The EF2800i will power anything from power tools to sophisticated electronic equipment. Powerful enough to use for home backup and the inverter technology means you can run anything from it. Use it from the job site to home and on the road.

## KEY FEATURES

- Electric Circuit Breaker
- 4-Stroke OHV Engine
- Oil Warning System
- Auto Decompressor
- Independent Fuel Tap
- Brushless Alternator
- Spark Arrestor
- Fuel Gauge



Overseas model shown.

INVERTER GENERATORS