

SPECIFICATIONS	EF6300iSE
Type	Inverter
Rated Voltage	230V
Frequency	50Hz
Rated Output	5500 Watts
Max Output	6300 Watts
DC Output	None
Engine Type	OHV MZ360 Air Cooled
Displacement	357cc
Max Output	6.6kW (9hp) @3400rpm
Starting System	Electric
LxWxH (mm)	780x616x692
Dry Weight	91kg
Fuel Tank Capacity	17L
Operating Hours (1/4 Load)	12.6hr (Eco On)
Noise Level (1/4 Load)	58dBA (7m)
Noise Level (Full Load)	65dBA (7m)
Brushless Alternator	•
Auto Decompressor	•
Electric Starter	•
Circuit Breaker	Electronic
Fuel Level Gauge	•
Oil Level Warning	•
Voltage Meter	•
Pilot Lamp	•
Noise Block™	•
Economy Idle Control	•
Twin Tech™ (Parallel Use)	
Transportation Kit	Standard with wheels
Remote Starter Kit	Optional
AC Plug	•
DC Charging Cord	

## EF6300iSE

### 6.3KVA INVERTER GENERATOR

The all new EF6300iSE is the most powerful, most advanced Yamaha inverter generator ever!

The EF6300iSE quietly cranks out up to 6.3KVA of power to confidently run high-demand items like pumps and air conditioners, as well as sensitive equipment like plasma TVs and computers. Advanced features include electric start and optional wireless remote, to provide you with everything you'd expect from Yamaha in one beautiful, powerful and compact package.

#### KEY FEATURES

- Electric Circuit Breaker
- 4-Stroke OHV Engine
- Oil Warning System
- Auto Decompressor
- Independent Fuel Tap
- Brushless Alternator
- DC Output Capability
- Spark Arrestor
- Noise Block™
- Fuel Gauge
- Electric Starter



Overseas model shown.

INVERTER GENERATORS